



Shown actual size: Maestro Wireless dimmer and 1-gang Claro wallplate in White (WH).

Shown actual size: Pico wireless remote in White (WH), W: 1.25 in (31.75 mm) x H: 2.63 in (66.68 mm) x D: .33 in (8 mm). For details, see p. 178)

Product family features

- Combine up to 10 wireless devices (dimmers, switches, sensors and/or wireless remotes)
- True multi-location dimming from every location
- Tap on to favorite level; tap off; tap twice for full on
- Touch rocker to adjust light level
- Delayed off provides light as you exit the room
- C•L® model available
- Communicates at 434 MHz frequency
- Coordinating Claro®, Satin Colors®, and Stainless Steel wallplates only available separately

Control types

- Single-pole (one location)
- Multi-location (up to 10 locations)
- Wireless multi-location (up to 10 locations)

Direct load type compatibility

- Incandescent/halogen lighting
- Dimmable CFL/LED lighting (screw-base)
- Magnetic low-voltage lighting
- Electronic low-voltage lighting
- Fluorescent lighting
- LED lighting
- Switched lighting/fan/motor



Available finishesUse **BOLD** color code in model number (Example: MRF2-600M-**PD**)

Gloss finishes*

**WH**
White**LA**
Light Almond**AL**
Almond**IV**
Ivory**GR**
Gray**BR**
Brown**BL**
Black

Satin Colors® finishes*

**SW**
Snow**LS**
Limestone**BI**
Biscuit**ES**
Eggshell**PD**
Palladium**TP**
Taupe**ST**
Stone**BG**
Bluestone**PL**
Plum**SG**
Sea Glass**TQ**
Turquoise**GS**
Goldstone**DS**
Desert Stone**GB**
Greenbriar

Metal finish wallplate**

**MS**
Mocha Stone**TC**
Terracotta**SI**
Sienna**HT**
Hot**MR**
Merlot**MN**
Midnight**SS**
Stainless Steel

Digital fade wireless dimmers



- Tap on to preset level; tap off
- Tap twice for full on
- Press, hold, and release for delayed fade-to-off
- Touch rocker to adjust light level
- Provides true dimming from each location with companion dimmers or Pico® wireless remotes
- C•L® dimmer offers reliable dimming of dimmable CFLs/LEDs, as well as halogens and incandescents



Incandescent/halogen dimmer



Dimmable CFL/LED (screw-base) dimmer

Digital fade wireless C•L® dimmer*

Multi-location/single-pole MRF2-6CL-**XX**¹
120V 600W (Inc) 150W (CFL/LED)

Visit **www.lutron.com/dimcflled** for an approved list of dimmable CFL/LED bulbs, and how to calculate wattage when mixing lamp types.

Adjustable low-end trim.



Incandescent/halogen dimmers

Digital fade wireless dimmer*

Multi-location/single-pole MRF2-600M-**XX**¹
120V 600W

Digital fade wireless dimmer*, Pico® wireless remote and wallplate

Multi-location/single-pole MRF2-600MTHW-WH
120V 600W



Incandescent/halogen dimmer



Magnetic low-voltage dimmer

Digital fade wireless dimmer*

Multi-location/single-pole MRF2-6MLV-**XX**¹
120V 600W (Inc)
600VA/450W (MLV)

Digital fade wireless dimmer—
specification grade*

Multi-location/single-pole MRF2-10D-120-**XX**¹
120V 1000W (Inc)
1000VA/800W (MLV)

The stated W (Watt) rating is the maximum incandescent lamp load. Ratings for MLV loads represent the maximum of the total lamp wattage plus MLV transformer loss (typically 20%).

XX¹: Gloss and Satin Colors® codes, see p. 153

* Minimum load required, see specification submittal

**Incandescent/halogen dimmer****Magnetic low-voltage dimmer****Hi-lume® 1% 2-wire LED driver dimmer****Tu-Wire® fluorescent ballast dimmer**

Digital fade wireless dimmer—
specification grade^{*,**}

Multi-location/single-pole MRF2-6ND-120-**XX**¹
120 V 600 W (Inc)
600 VA/450 W (MLV)
350 W (Hi-lume 1% LED driver, max. 8)
5 A (Tu-Wire fluorescent ballast)

The stated W (Watt) rating is the maximum incandescent lamp load. Ratings for MLV loads represent the maximum of the total lamp wattage plus MLV transformer loss (typically 20%).

Compatible with Advance Mark X and Sylvania POWERSENSE fluorescent ballasts, in addition to Lutron Tu-Wire®

Setting the low-end trim is necessary to ensure optimal dimming performance when using with LED drivers and fluorescent ballasts. For more information consult Lutron Application Note #370, Maestro Wireless Advanced Programming Mode, at www.lutron.com/applicationnotes

**Electronic low-voltage dimmer**

Digital fade wireless dimmer^{*}

Multi-location/single-pole^{*} MRF2-6ELV-120-____
120 V 600 W

**3-wire fluorescent ballast/LED driver dimmer**

Digital fade wireless dimmer^{*}

Multi-location/single-pole MRF2-F6AN-DV-**XX**¹
120/277 V 6 A

For use with Hi-lume 1% and EcoSystem® ballasts, and Hi-lume 1% and Hi-lume Premier 0.1% LED drivers.

For more information on Hi-lume 1% LED drivers, visit www.lutron.com/HilumeLED.

Adjustable low-end trim.

***Requires neutral wire connection**

****Minimum load required, see specification submittal**