



HOTSPOT

FULHAM



EZ Exit LED Emergency System

The cost-saving alternative to traditional emergency fixtures



- Fits seamlessly into standard T-grid ceilings
- Lower installation costs than “bug eye” emergency lights
- High lumen output reduces the number of fixtures required to meet emergency lighting regulations
- Integrated test switch, multiple mounting options

Fulham's new HotSpot EZ Exit Emergency System is changing the way people think about emergency lighting. High output linear LED strips install quickly in standard T-grid ceilings, with constant power emergency drivers mounted out of sight above the grid. During normal standby operation the EZ Exit system is almost invisible, but when the power goes out the LED strips automatically illuminate, providing at least 90 minutes of emergency lighting. EZ Exit kits are available in 24" and 48" module lengths, and include all the installation hardware required to turn a standard T-grid ceiling into a reliable LED emergency lighting solution.



Normal conditions



Power outage - emergency LEDs activated

Specifications

Input Voltage	100-277VAC, 50/60Hz	Output Type	Class 2
Recharge Time	24 Hours	Surge Protection	Per C62.41 (TVS)
Emergency Operation	90 Minutes	Protective Lens	1.2mm Frosted Polycarbonate V-0 Flame rated
Operating Temp. Range (Ta)	0°C to 50°C / 32°F to 122°F	Lens Transmittance	15%
Module Case Temperature (Tc)	Tc max 90°C / 194°F	PCB Material	FR4
Estimated Lumen Maintenance	L70: >60,000Hrs / L90: 40,000Hrs	Warranty	5 years from the manufacture date
RFI/EMI	FCC PART15A Non-Consumer		

Product Models

Model number	Max Input Current (A)	Nominal Input Power (W)	Output Power (W)	Module Operating Voltage (VDC)	Max Lumen Output (lm)	Battery	Dimensions (L x W x H)
FHEZ10A24	0.087	5.7	10.7	26.2	1300	NiCd 9.6Vdc	23.9" x 1.44" x 1.86" 607mm x 26mm x 47mm
FHEZ10A24-CEC*							
FHEZ17A48	0.11	7.9	17	25.8	2200	NiCd 14.4Vdc	47.9" x 1.44" x 1.86" 1217mm x 26mm x 47mm
FHEZ17A48-CEC*							

* CEC Title 20 Compliant

All EZ Exit Kits include EZ Exit emergency luminaire, HotSpot Constant Power emergency driver, 10' extension harness, and necessary installation hardware

Installation Savings

High lumen EZ Exit luminaires versus traditional bug eye emergency lighting in a standard 60-ft hallway

	4-ft EZ Exit	Typical Bug Eye Emergency Fixture
		
 Quantity Required	2	8
 Total Installation Time (hrs)	2	16
 Total Installation Cost (at \$65/hr)	\$130	\$1040

Visit Fulham.com for video of the EZ Exit in action and to download installation instructions

FULHAM www.fulham.com
North America • China • Europe • India • Latin America

Fulham Headquarters: 12705 S. Van Ness Avenue, Hawthorne, CA 90250 Tel: +1 (323) 599-5000 Fax: +1 (323) 754-9060 • order@fulham.com

All trademarks are the property of their respective owners | ©Fulham Co. Inc., 2019 | PN: FLYER-HS-EZEXIT | REV: SEP19