

NL-671
6" Gimbal Ring with Metal Trim

FEATURES

- Trim:** Adjustable metal gimbal ring can be adjusted up to 35°.
- Mounting:** Trim includes two "V" torsion springs to mount trim securely to housing. Replacement "V" torsion springs are available, specify NRA-86.
- Wiring:** Trim includes terminal block with 6-1/2" spade connectors for AR111 or PAR36 lamp. Simply cut MR16 lead wires and connect into open terminal block slots. Replacement terminal block with spade connectors are available, must specify NRA-6003.

COMPATIBLE HOUSINGS

Compatible with Low Voltage housings and Low Voltage Retrofit Kit. See individual specification sheets for more information.

LAMP

- Low Voltage**
50W 12V AR111 (NLIC-601 Series; NL-601 Series; NLR-604 Series)
50W 12V PAR36 (NLIC-601 Series; NL-601 Series; NLR-604 Series)

LABELS AND LISTINGS

cULus Listed for Damp Location when used with compatible housing.



Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT IMAGES AND DIMENSIONS



6" Gimbal Ring with Metal Trim

Catalog No. _____

NL-671W = Gimbal Ring with White Metal Trim

Compatible Housings

Low Voltage
Catalog No.
NLIC-601QAT = 6" ICAT New Construction - 120V Magnetic / 50W max.
NLIC-601/1EL = 6" ICAT New Construction - 120V Electronic / 50W max.
NLIC-601/2EL = 6" ICAT New Construction - 277V Electronic / 50W max.
NL-601Q = 6" Non-IC Air-Tight New Const. - 120V Magnetic / 50W max.
NL-601/75Q = 6" Non-IC Air-Tight New Const. - 120V Magnetic / 75W max.
NL-601/1EL = 6" Non-IC Air-Tight New Const. - 120V Electronic / 50W max.
NL-601/75/1EL = 6" Non-IC AT New Const. - 120V Electronic / 75W max.
NL-601/2EL = 6" Non-IC Air-Tight New Const. - 277V Electronic / 50W max.
NL-601/75/2EL = 6" Non-IC AT New Const. - 277V Electronic / 75W max.
NLR-604Q = 6" Non-IC Air-Tight Remodel - 120V Magnetic / 50W max.
NLR-604/75Q = 6" Non-IC Air-Tight Remodel - 120V Magnetic / 75W max.
NLR-604/1EL = 6" Non-IC Air-Tight Remodel - 120V Electronic / 50W max.
NLR-604/75/1EL = 6" Non-IC AT Remodel - 120V Electronic / 75W max.
NLR-604/2EL = 6" Non-IC Air-Tight Remodel - 277V Electronic / 50W max.
NLR-604/75/2EL = 6" Non-IC AT Remodel - 277V Electronic / 75W max.

Example: NL-671W = 6" Gimbal Ring with White Metal Trim