



Micro-Quick® Control Connectors
Dual Key 2 - 6 Pole Receptacles

1/4" NPT Rear Thread Receptacle




	MALE	FEMALE
A	0.75 (19.1)	0.75 (19.1)
B	0.75 (19.1)	0.86 (21.8)
C	0.10 (2.5)	0.10 (2.5)
D	12.0 (304.8)	12.0 (304.8)
E	0.62 (15.8)	0.62 (15.8)
F	0.35 (8.9)	0.38 (9.7)

1/2" NPT Rear Thread Receptacle



	MALE	FEMALE
A	1.00 (25.4)	1.00 (25.4)
B	1.00 (25.4)	1.00 (25.4)
C	0.24 (6.10)	0.24 (6.1)
D	12.0 (304.8)	12.0 (304.8)
E	0.87 (22.1)	0.87 (22.10)
F	0.46 (11.7)	0.46 (11.7)
G	0.85 (21.6)	0.85 (21.6)

Female Inverse Receptacle
1/4" NPT Rear Thread



A	0.75 (19.1)
B	0.86 (21.8)
C	0.15 (3.8)
D	12.0 (304.8)
E	0.62 (15.8)
F	0.40 (10.2)
G	0.56 (14.2)

All dimensions are shown in inches (mm)

Conductor Color Code - Dual Key

Contact Number	2 Pole	3 Pole	4 Pole	5 Pole	6 Pole
1	Brown	Green	Red/Black	Red/White	Red/White
2	Blue	Red/Black	Red/White	Red	Red
3		Red/White	Red	Green	Green
4			Green	Red/Yellow	Red/Yellow
5				Red/Black	Red/Black
6					Red/Blue

ACCESSORIES

Dust Caps

Closure caps protect plugs and receptacles when not in use. Thread is 1/2-20 UNF.

Catalog #	
MRCM2	
MPCM2	